


Potentiometer-controlled LED dimmer, high-side switched

Article number PR142x02



The PR142x02 converts the position of an external potentiometer from 500 Ω to 100 k Ω into a high-side switched PWM output: the lamp is connected between terminal 2 and terminal 6. The potentiometer is connected to terminals 3, 4 and 5. Terminal 6, the supply minus, also serves as the common ground for the analogue signals; the module is not galvanically isolated.


Price on request. Lead time on request. Not in stock? We will make it.

Specifications

Supply	9 to 30 V DC, for 12 and 24 V DC systems
Input	Potentiometer from 500 Ω to 100 k Ω on terminals 3, 4 and 5
Output	PWM, high-side switched: lamp between terminals 2 and 6
Isolation	Not isolated: terminal 6 (supply minus) is also the common ground for the analogue signals
Output current	5 A max.
PWM frequency	122 Hz
Ambient temperature	0 to 80 °C
Dimensions	45 x 82 mm

Connections

Terminal 1	Supply plus (12 or 24 V DC)
Terminal 2	PWM output, to the lamp plus
Terminal 3	Potentiometer plus
Terminal 4	Potentiometer signal (wiper)
Terminal 5	Potentiometer minus
Terminal 6	Supply minus and lamp minus, also common ground for the analogue signals



More information, price and lead time: www.procircuits.nl/en/products/pr142x02

ProCircuits B.V. · Van Nijenrodeweg 903, 1081 BJ Amsterdam, Netherlands · +31 6 45 77 55 93 · willem@procircuits.nl ·
Chamber of Commerce (KVK) 87009870

We supply businesses only.