


Pulse-contact LED dimmer, low-side switched

Article number PR142x03



The PR142x03 converts the pulses of an external pulse contact into a low-side switched PWM output: the lamp is connected between terminal 1 (supply plus) and terminal 2. The switch or pulse contact is connected between terminals 4 and 5, so the lighting is dimmed with a single button. Terminal 6, the supply minus, also serves as the common ground for the signals; the module is not galvanically isolated.


Price on request. Lead time on request. Not in stock? We will make it.

Specifications

Supply	9 to 30 V DC, for 12 and 24 V DC systems
Input	Pulse contact or switch between terminals 4 and 5
Output	PWM, low-side switched: lamp between terminals 1 and 2
Isolation	Not isolated: terminal 6 (supply minus) is also the common ground for the signals
Output current	5 A max.
PWM frequency	122 Hz
Ambient temperature	0 to 80 °C
Dimensions	45 x 82 mm

Connections

Terminal 1	Supply plus (12 or 24 V DC) and lamp plus
Terminal 2	PWM output, to the lamp minus
Terminal 3	Not used
Terminal 4	Pulse contact (signal plus): one side of the switch
Terminal 5	Pulse contact (signal minus): other side of the switch
Terminal 6	Supply minus, also common ground for the signals



More information, price and lead time: www.procircuits.nl/en/products/pr142x03

ProCircuits B.V. · Van Nijenrodeweg 903, 1081 BJ Amsterdam, Netherlands · +31 6 45 77 55 93 · willem@procircuits.nl ·
Chamber of Commerce (KVK) 87009870

We supply businesses only.